

FiberRack FLR-16

16 slot Converter Chassis System

Features

- Plug & Play
- Provide housing for up to 16 media converters
- Standard 19" rack-mount size, 3U height
- Hot swappable, easy & quick replacement of converters and power supplies
- Bay power isolation, ensure each bay is electrically isolated from each other
- Two redundant power supplies with load-sharing to ensure reliable operation
- Power isolation design with converters bays: ensure each bay is electrically isolated from each other



Specifications

Capacity	<ul style="list-style-type: none"> • 16 bays for housing up to 16 media converters
Power	<ul style="list-style-type: none"> • One hot-swappable power supply, optional second power supply for load-sharing, hot-swappable • Input: AC 90~260VAC/50~60Hz, 2A
Diagnostic LED	<ul style="list-style-type: none"> • Link, Speed and Duplex
Cooling	<ul style="list-style-type: none"> • One fans mounted at the rear
Temperature	<ul style="list-style-type: none"> • Operating – 0°C to 60°C • Storage – -20°C to 70°C
Humidity	<ul style="list-style-type: none"> • Operating -10% to 90% RH • Storage -5% to 90% RH
Dimension	<ul style="list-style-type: none"> • 440mm*220mm*300mm(L*H*W)
Regulatory Compliance	<ul style="list-style-type: none"> • FCC & CE

Ordering Information

FLR-16: 19" Chassis System for up to 16 media converters(media converter not included)

** Product specification subject to change without notice.*